

L9.1E / L9.2E	East Europe, Mono/Stereo	Wk908.5 or higher	SAA5560/M2/024	L90ET2-1.0	9352 634 41112	Yes	Only suitable in combination with ST24W08CB1 (4822 209 13052)	L90ET2-1.2	9352 639 96112
L9.1E / L9.2E	East Europe, Mono/Stereo	Wk923.5 or higher	SAA5560/M2/056	L90ET2-1.2	9352 639 96112	Yes	Only suitable in combination with ST24W08CB1 (4822 209 13052)	L90ET2-1.2	9352 653 79112
L9.1E / L9.2E	East Europe, Mono/Stereo	Wk939.5 or higher	SAA5560/M3/1056	L90ET2-1.2	9352 653 79112	Yes	Only suitable in combination with ST24W08CB1 (4822 209 13052)	L90ET2-1.4	9352 672 87112
L9.1E / L9.2E	East Europe, Mono/Stereo 5p-txt	Wk008.1 or higher	SAA5560/M3/187	L90ET2-1.4	9352 672 87112	Yes	Issues solved : - Set ITT DC_NOTCH register to ON always. - Status of Scart2 is not read when option 2X=OFF. This eliminates the need to ground - When the user press the up/down arrow key (and provided that the 16:9/4:3 feature is available), monitoring the voltage level on scart pin 8 for change in aspect ratio is stopped. - Keep AFC window large for N2 Bimos TDA884x when not in auto/manual search. - Set goes into Compair mode only after video appears when AS=OFF. - When the user switches manually to AV, the statuses of Pin 8 transitions on both scart are ignored. New: - Improve NICAM reception algorithm, by auto forcing NICAM sound to mono on. - Disable overvoltage trigger (Bimos PRD) for at least 120ms after power on. - Access to SDM during cold start by shorting Pin 1 of EEPROM ST24W0x is removed. Shorting of Pin 20 of Painter (P0.6 for LED) during cold start will cause the software to enter SDM instead of SAM. (One can later toggle between SAM and SDM by pressing the local keys V- & P- simultaneously; this is an existing feature.) This change is to allow alternative tuning.	N.A.	N.A.