# Uputstvo za podešavanje ZyXEL P-660HW-T1 ADSL rutera



## Sadržaj Vašeg pakovanja

- Jedan ZyXEL Ruter
- Jedan DC strujni adapter
- Jedan mrežni kabl
- Jedan telefonski kabl
- Jedan ADSL spliter

Napomena: Molimo Vas proverite da li Vaše pakovanje sadrži sve gore navedene stavke.

### KORAK 1. FIZIČKO POVEZIVANJE ADSL RUTERA

ADSL spliter povežite **direktno** na telefonsku liniju kablom koji ide u port "**Line**" na spliteru. Iz porta "**Phone**" izvedite telefonski kabl na koji ćete povezati Vaš telefonski aparat. Iz porta "**ADSL**" ("Modem") izvedite telefonski kabl koji ćete povezati sa Vašim ADSL uređajem. Ethernet (mrežni) kabl povezati iz "Ethernet" porta u ADSL uređaju u "Ethernet" port na vašem računaru. Svi telefonski aparati moraju da budu povezani preko splitera. Ukoliko nisu povezani preko splitera, svaki telefonski aparat mora imati postavljen mikrofilter.

#### ADSL ruter se priključuje na telefonsku liniju na način prikazan na slici:



#### KORAK 2: KONFIGURISANJE RUTERA

Pokrenite internet pretraživač (Internet Explorer, Mozilla, Opera, Safari...), zatim u polju za unos adrese unesite: **192.168.1.1** 

Avigatio	n Canceled - Windows Internet Explorer
00-	E http://192.168.1.1

Nakon ovog postupka, pojaviće vam se prozor u koji ćete upisati **password** za pristup ruteru. Potrebno je upisati sifru: **1234** 

Kliknuti na LOGIN.

	P-660R-T	3 v2		
Welcome t	o your router Co	nfiguration Interf	ace.	
Enter your pa	assword and pres	is enter or click "I	Login".	
Password	:			
	Login	Cancel		

Nakon ovog postupka pojaviće se prozor za promenu šifre za pristup uređaju. Ukoliko ne želite da promenite šifru, kliknite na **IGNORE.** 

Use th	is screen to	change the pa	assword.
Your router is curren from unauthorized u Please select a new others to guess. We difficult for an intrud Enter your new pass click "Ignore" to kee	itly using the defi- sers we suggest password that wi suggest you con- er to guess. word in the two f p the default pas	ault password. To you change your p II be easy to reme nbine text with nu ields below and cl sword	protect your network assword at this time mber yet difficult for mbers to make it mo ck "Apply". Otherwise
New Password:	1		
Retype to Confirm			1

Zatim je potrebno odabrati vrstu podešavanja rutere, obeležite opciju **Go to Advanced setup.** Zatim kliknite na **Apply**.

he Wizard setup walks you through the most common configuration setting: /e suggest you use this mode if it is the first time you are setting up your outer or if you need to make basic configuration changes.
se Advanced mode if you need access to more advanced features not icluded in Wizard mode.
Go to Wizard setup
Go to Advanced setup
Click here to always start with the Advanced setup.
o to Wizard setup o to Advanced setup ck here to always start with the Advanced setup.

Sada ste pristupili statusnoj stranici. Klikom na **Network**, izaberite opciju **WAN**. Time ste pristupili podešavanju samog uređaja.

😸 .:: Welcome to the Web-Based Co	onfigurator:: Windows Internet Explorer		100			) X
🕒 🗢 🙋 http://192.168.1.1	L/rpSys.html			👻 😽 🗙 🚮 Go	ogle	٩
<u>File Edit View Favorites ]</u>	<u>I</u> ools <u>H</u> elp					
🙀 🏼 🏉 .:: Welcome to the Web-B	ased Configurator::.			1 · 1	* 🖃 🖶 * 🗗 🖉 *	• 🔞 🕶
ZyXEL						1
2	Status					
				Refresh Interval: None	▼ Apply	
Status						
	Device Information		System Status			
P-660HW-T1 v3						
Network	Host Name:		System Uptime:	0:00:34		
-wan	Model Number:	P-660HW-T1 v3	Current Date/Time:	01/01/2000 00:00:44		
	MAC Address:	40:4a:03:bf:90:7e	System Mode:	Routing / Bridging		
LAN	ZyNOS Firmware Version:	V3.70(BJZ.2)   7/31/2009	CPU Usage:		17.70%	
- Wireless LAN	DSL Firmware Version:	DMT FwVer: 3.11.2.64_A_TC	Memory Usage:		62%	
NAT	WAN Information					
	- DSL Mode:	Error				
E Security	- IP Address:	<u>0.0.0.0</u>	Interface Status			
Advanced	- IP Subnet Mask:	0.0.0.0				
Maintenance	- Default Gateway:	N/A	Televis	Chalues	Dete	
	- VPI/VCI	8/35	Interface	Status	кате	
	LAN Information		DSL	Down	0 kbps / 0 kbps	
	- IP Address:	192.168.1.1	LAN	Up	100M/Full Duplox	
	- IP Subnet Mask:	255.255.255.0	DAN	op	100M/Tuli Duplex	
	- Unice: WI AN Information	Server	WLAN	Active	54M	
	SEID:	a ust or have connected the phan				
	- 331D:	e vec or have connected the phon				
	- Channell	WRA-BEK	Summary			
	- WPS:	Upconfigured				
	- Status:	On	Client List	A. 10 T. I	12	
	Security		Client List	AnyIP Tab	ne station	
	- Firewall:	Enabled	WLAN Status	Packet Sta	ausues	
	- Content Filter:	Disable				
	# Message Ready					
Done				Internet   Protected Mode: C	)ff 🖓 👻 🔍 10	• %00

Podešavanje rutera podrazumeva popunjavanje sledećih parametara:

Internet Access Setup More Connections		Modulation:Multi Mode
Line		
Modulation	Multi Mode 👻	Mode: Routing
General		
Mode Encapsulation User Name	Routing  PPPoE  username@sezampro	Encapsulation: PPPoE
Password		U.S. News Levis 11 States
Service Name	Orion Telekom ADSL	User Name: korisnicko_ime@sezampro
Multiplexing Virtual Circuit ID	LLC 🖵	Password: otkucajte šifru koju ste dobili
VPI	8	nrilikom potnisivanja ugovora
VCI	35	prinkom potpisivanja ugovora
IP Address		
Obtain an IP Address Automatically     O Static IP Address     IP Address     IP Address     IP Address	0.0.0.0	Service Newser Orign telehore ADSI
DNS server		Service Name: Orion telekom ADSL
		Multipleving, LLC
First DNS Server	Obtained From ISP 🖉 0.0.0.0	Multiplexing. LLC
Second DNS Server	Obtained From ISP 🖕 0.0.0.0	Virtual Circuit ID:
Third DNS Server	Obtained From ISP 🖕 0.0.0.0	
Connection		
		<b>VCI:</b> 35
Nailed-Up Connection		
Connect on Demand	Max Idle Timeout 0 sec	
	Apply Cancel Advanced Setup	Treba ostaviti označeno polje Obtain an IP address Automatically

Kliknite na Apply. Nakon ovih podešavanja trebalo bi da imate pristup Internetu.

# KORAK 3: PODEŠAVANJE WI-FI MREŽE

Ukoliko u početnom meniju Network izaberete opciju Wireless LAN, moći ćete da podesite Vašu Wireless mrežu. Na slici je dat postupak podešavanja:

	Network > Wireless LAN > AP	
Status	AP More AP WPS WPS Station WDS Scheduling	
P-660HW-T1 v3 E-Network	Wireless Setup	
WAN	Carlie Wireless LAN	
LAN	O Auto-Scan Channel	
- Wireless LAN	Channel Selection     Channel-	6 2437MHz 🔻 Scan
NAT	Common Setun	
-Security	common secup	<b>Network Name(SSID):</b> upišite
-Advanced	Network Name(SSID) ime_Vase_Wi	ime Vaše WiFi mreže
-Maintenance	Hide SSID	(proizvoljno)
	Security Mode WPA-PSK 🔻	
	Pre-Shared Key	Security Mode: WPA-PSK
	ReAuthentication Timer 1800 (In	Seconds)
Contraction of the local division of the loc	Idle Timeout 3600 (In	Seconds) <b>Pre-Shared Key:</b> upišite šifru
	Group Key Update Timer 1800 (In	seconds) uz pomoć koje ćete se
	MAC Filter Deny Associat	ion Edit konektovati na Vašu Wi-Fi
	QoS None Default	• mrežu
	Apply Canc	el Advanced Setup
li i		

Podešavanja se potvrđuju klikom na APPLY. Nakon ovoga Vaš ruter je podešen i možete koristiti Internet.