

Uputstvo za **Windows XP** (za korisniike **postpaid-a**, a uz male korekcije i za korisnike **pripaid-a**):

- 1) Flešovati telefon na verziju software-a SW20 (probati i sa verzijama SW12, SW13 i SW16, ali sa SW20 radi provereno). To možete uraditi u servisu "ROAMING" ulica Milana Rakića 8, Beograd (telefon: 011/380-95-50). Verzija software-a na telefonu Siemens C60 se može proveriti kucanjem šifre: ***#06#** > **Info** i videćete između ostalog i **SW-Version**.
- 2) Instalirati drajver za "Standard 56000 bps V90 Modem" (MODEM.INF). Windows XP nema ovaj drajver na spisku svojih standardnih modem drajvera, pa ga treba naknadno instalirati: **Control Panel > Phone and Modem Options > Modems > Add...**Čekirati: **Don't detect my modem; I will select it from a list**, zatim **Next**, pa **Have Disk...**i pronaći lokaciju na kojoj ste sačuvali drajver **MODEM.INF**. Izabrati drajver **MODEM.INF** pa **Next**. Bez obzira što ovaj drajver nije "Digitally signed", instalirati ga (**Continue anyway...**). Izabrati "Standard 56000 bps V90 Modem" i instalirati ga na **COM 1** port.
- 3) Za vezu sa računarom koristiti originalni DC-510 USB kabl ili srediti serijski Data kabl koji ste dobili uz telefon. Sledi uputstvo za serijski Data kabl: sve što treba uraditi jeste da se odstrani kontakt na **PIN1** na **SubD9** konektoru. Pinovi su obeleženi, i na svakom postoji metalni kružić (metalni kontakt koji prenosi signal kada se kabl priključi na računar). Za odstranjivanje kontakta koristiti minijaturnu bušilicu i burgiju od 2mm. Pažljivo razbušiti rupu gde se nalazi PIN1 (na taj način se onemogućava uspostavljanje kontakta sa PIN1 kontaktom na računaru). Ako sve ovo izgleda komplikovano, odneti kabl u servis "ROAMING" da vam oni to srede (ukoliko ste telefon kupili u Telekomu imate garanciju uz koju je servisiranje u "ROAMING"-u besplatno).
- 4) Na računaru srediti podešavanja kako je prikazano u donjoj tabeli.
- 5) Prilikom konektovanja koristiti modem pod nazivom "Standard 56000 bps V90 Modem".
- 6) Uživate u surfu preko mobilnog!

Podešavanja Modema:

Control Panel > Phone and Modem Options > Modems > Standard 56000 bps V90 Modem (COM1) > Properties >

General >

ništa ne menjati

Modem >

Speaker volume.....On

Maximum port speed..... 115200

Dial control.....Wait for dail tone before dailing - čekirano

Diagnostics >

ništa ne menjati

Advanced >

Extra Settings > Extra initialization commands.....uneti sledeće: +cgdcont=1,"IP","gprsinternet"

(kod pripaid-a je malo drugačije: umesto "gprsinternet" potrebno je uneti "mms", kao i u APN na telefonu gde treba kucati: mms umesto gprswap. Podrazumeva se da je MMS aktiviran)

Driver >

ništa ne menjati

Podešavanja COM porta preko koga je telefon priključen na računar:

Control Panel > System > Hardware > Device Manager > Ports (COM & LPT) > Communication Port (COM1) > Properties >

Port Settings >

Bits per second.....115200

Data bits.....8

Parity.....None

Stop bits.....1

Flow control.....Xon/Xof

Port Setings > Advanced

sva podešavanja na maksimum (do kraja)

Ostalo ne menjati.

Podešavanje konekcije (instalacija konekcije):

Control Panel >

Network Connections >

Create a new connection > Next >

Connect to the Internet > Next >

Set up my connection manually > Next >

Connect using a dial up modem > Next >

Modem - Standard 56000 bps V90 Modem (COM1) - izabrati (čekirati) > Next >

ISP Name: mts064.gprs > Next >

Phone number: *991# > Next >**

User name: mts, Password: 064, Confirm Password: 064, ostalo sve čekirano > Next >

Finish.

Ivan Milović

ivanmilovic@hotmail.com