



Kapacitet kondenzatora u mF uz napon jednofazne mreže			Snaga motora u KS
110	220	380	
14	5	2.5	0.1
28	10	4	0.2
43	15	6	0.3
58	20	8	0.4
72	24	9	0.5
88	29	10	0.6
100	33	12	0.7
118	39	14	0.8
130	44	16	0.9
145	48	18	1.0
158	53	19	1.1
172	59	20	1.2
186	63	22	1.3
202	69	23	1.4
218	73	25	1.5

SPOJ TROFAZNOG ELEKTRICNOG MOTORA NA JEDNOFAZNU ELEKTRICNU MREZU

DRAWN	X	SCALE	1:1	SHEET	1 OF 1
-------	---	-------	-----	-------	--------

SIZE	FSCM NO	DWG NO	REV
------	---------	--------	-----